

# WallyAzimuth Volt to Decibel Conversion Chart

Volts	dB	Volts	dB	Volts	dB
10,000	60,0	0,794	38,0	0,063	16,0
9,441	59,5	0,750	37,5	0,060	15,5
8,913	59,0	0,708	37,0	0,056	15,0
8,414	58,5	0,668	36,5	0,053	14,5
7,943	58,0	0,631	36,0	0,050	14,0
7,499	57,5	0,596	35,5	0,047	13,5
7,079	57,0	0,562	35,0	0,045	13,0
6,683	56,5	0,531	34,5	0,042	12,5
6,310	56,0	0,501	34,0	0,040	12,0
5,957	55,5	0,473	33,5	0,038	11,5
5,623	55,0	0,447	33,0	0,036	11,0
5,309	54,5	0,422	32,5	0,034	10,5
5,012	54,0	0,398	32,0	0,032	10,0
4,732	53,5	0,376	31,5	0,030	9,5
4,467	53,0	0,355	31,0	0,028	9,0
4,217	52,5	0,335	30,5	0,027	8,5
3,981	52,0	0,316	30,0	0,025	8,0
3,758	51,5	0,299	29,5	0,024	7,5
3,548	51,0	0,282	29,0	0,022	7,0
3,350	50,5	0,266	28,5	0,021	6,5
3,162	50,0	0,251	28,0	0,020	6,0
2,985	49,5	0,237	27,5	0,019	5,5
2,818	49,0	0,224	27,0	0,018	5,0
2,661	48,5	0,211	26,5	0,017	4,5
2,512	48,0	0,200	26,0	0,016	4,0
2,371	47,5	0,188	25,5	0,015	3,5
2,239	47,0	0,178	25,0	0,014	3,0
2,113	46,5	0,168	24,5	0,013	2,5
1,995	46,0	0,158	24,0	0,013	2,0
1,884	45,5	0,150	23,5	0,012	1,5
1,778	45,0	0,144	23,0	0,011	1,0
1,679	44,5	0,133	22,5	0,011	0,5
1,585	44,0	0,126	22,0	0,010	-
1,496	43,5	0,119	21,5		
1,413	43,0	0,112	21,0		
1,334	42,5	0,106	20,5		
1,259	42,0	0,100	20,0		
1,189	41,5	0,094	19,5		
1,122	41,0	0,089	19,0		
1,059	40,5	0,084	18,5		
1,000	40,0	0,079	18,0		
0,944	39,5	0,075	17,5		
0,891	39,0	0,071	17,0		
0,841	38,5	0,067	16,5		